arXiv:1203.2456v2 [cs.IT] 21 Mar 2012

On Secrecy above Secrecy Capacity

R Rajesh
CABS, DRDO
Bangalore, India
Email: rajesh81r@gmail.com

Shahid M Shah
Dept. of ECE
Indian Institute of Science
Bangalore, India
Email: shahid@ece.iisc.ernet.in

Vinod Sharma
Dept. of ECE
Indian Institute of Science
Bangalore, India
Email: vinod@ece.iisc.ernet.in

***Abstract*—In this paper we provide schemes that achieve rates above the 'secrecy capacity' region on a Gaussian wire-tap channel. We take the probability of error as the measure of reliability at the intended receiver and also as the measure of secrecy at the eavesdropper. We show that any rate $0 < R < C = 0.5\log(1 + P/N)$ is achievable for this case using the usual random coding-decoding scheme. We also show the relation between probability of error and equivocation as considered in physical layer secrecy problems. We then extend the results to the fading channels.**

***Index Terms*—Probability of error, Physical Layer Secrecy, Equivocation, Strong converse.**

I. INTRODUCTION

Information theoretic security is being widely studied in recent times ([14], [3]). It provides fundamental limits of secret communication. Unlike in cryptography, the information theoretic techniques, are not based on complexity of computational hardness of certain problems. Information theoretic security can also be used in a system in addition to cryptographic techniques to add additional layers of protection to the information transmission or to achieve key agreement and/or distribution.

Information theoretic formulations for 'reliable communication' and 'secrecy' were provided in classic papers of Shannon [19] and [20]. A secret communication system model considers reliable transmission of information from the transmitter to the intended receiver and this information should not be decoded by the eavesdropper. Shannon characterized reliable communication using average probability of error and 'secrecy' using equivocation. The properties of equivocation are also discussed in [20]. Shannon considered the case of perfect secrecy when equivocation $H(W|Z^n) = H(W)$, where W is the message transmitted, and Z^n is the received symbol at the eavesdropper. This of course implies $I(W;Z^n) = 0$. A weaker form of equivocation as compared to Shannon is $I(W,Z^n) \to 0$ as $n \to \infty$ [3]. These are further weakened to $I(W;Z^n)/n \to 0$ in [16]. This implies that the average probability of error in the eavesdropper goes to 1.

In this set-up of 'secret communication' a natural definition of secrecy would be that the intended receiver decodes the message with average probability of error going to zero and the eavesdropper decodes the message with average probability of error going to one. Recently similar notion of secrecy is also considered in [2] to obtain lattice codes for secret communication. We consider this definition in the present paper and study the achievable rates on the Gaussian wiretap channel and show that this natural definition leads to improved rates. We also relate the probability of error at the eavesdropper to equivocation to relate this secrecy to the equivocation based secrecy. In the following we survey the related literature.

'Wiretap channel' introduced and studied by Wyner [23], captures the physical communication secrecy problem. 'Wiretap channel' is modelled as a degraded broadcast channel and assumes that the channel between the transmitter and the receiver is better than the channel from the transmitter to the eavesdropper. Wyner's work was extended by Leung and Hellman [15] to the Gaussian channel. Csiszàr and Körner [6] considers a general discrete memoryless broadcast channel, and shows that the secrecy capacity is positive if the main channel to the intended user is more capable than of the eavesdropper, and zero if the wiretapper's channel is less noisy. The secrecy over a fading channel was studied in [12]. In [4], a wire-tap channel with slow fading is studied where an outage analysis with full CSI of the eavesdropper and imperfect CSI of the eavesdropper was performed. It is shown that in wireless channels fading helps to provide secrecy rates even of the average SNR of the main channel is poor compared to the eavesdropper's channel.

Our notion of secrecy will be related to the equivocation based secrecy via converse results in Information Theory. Random coding arguments are used to prove capacity achievabiliy for a particular scheme and Fano's inequality is usually employed to show converse [5] that no scheme can give rates better than the capacity. The usual converse results consider average probability of error and are called 'weak converse'. Using 'weak converse' it is shown that for a discrete memoryless channel when $R > C$ the probability of decoding error is bounded away from zero [9]. The proof uses Fano's inequality. The strong converse shows that the maximum probability of decoding error of a MAP (Maximum A posterior Probability) decoder tends to one as block length goes to infinity [22]. A stronger form of converse was proved by Arimoto [1] where it is shown that at rates higher than capacity the average probability of error goes to one exponentially fast with the block length. This result was generalized to continuous alphabets and general measures in [18].

Fano's inequality provides a tight lower bound on the error probability in terms of the conditional entropy. A tight upper bound on the error probability in terms of conditional



Fig. 1. Wiretap channel

entropy is provided in [8] which also finds relations between probability of error in a MAP decoder and the conditional entropy. Relation between error probability and conditional entropy are also provided in [13].

The rest of the paper is organized as follows: In Section II, we define the model and notation. In Section III, we provide coding-decoding schemes for perfect secrecy and using average probability of error as the measure of both reliability and secrecy. We show that rates above equivocation based perfect secrecy capacity are achievable for a Gaussian channel. Section IV finds the relation between the chosen criterion of probability of error and equivocation. Section V extends the results to a Gaussian fading channel. We conclude the paper in section VI.

II. MODEL AND NOTATION

We consider a Gaussian Wiretap system where a transmitter Alice wants to communicate the message to a legitimate receiver Bob. There is also an eavesdropper, Eve, who is trying to get access to the message sent to Bob. The model is denoted in Figure 1. The transmitter chooses message W for transmission from a set $\mathcal{W} = \{1, 2, ..., M = 2^{nR}\}$ with uniform distribution. These messages are encoded into codewords $(X_1, ..., X_n)$ with a power constraint $E[X^2] \leq P$. At time i, Alice transmits X_i. Then Bob receives $Y_i = X_i + N_{1i}$ and the eavesdropper receives $Z_i = X_i + N_{2i}$. The noise sequences $\{N_{1i}\}$ and $\{N_{2i}\}$ are assumed to be independent of $\{X_i\}$ and also of each other. Also, we assume that $N_{1i} \sim \mathcal{N}(0, \sigma_1^2)$ and $N_{2i} \sim \mathcal{N}(0, \sigma_2^2)$ and $\sigma_1^2 < \sigma_2^2$. The decoder at Bob estimates the transmitted message as $\widetilde{W}$ from $Y^n \equiv (Y_1, ..., Y_n)$. It is assumed that Bob as well as Eve know the chosen codebooks. We use $P_e^n(B)$ and $P_e^n(E)$ to denote the average probability of decoding error for block length n at Bob and Eve respectively for the MAP decoder. Our secrecy requirement is that $P_e^n(B) \to 0$ and $P_e^n(E) \to 1$ as $n \to \infty$.

III. CAPACITY RESULTS

In this section we characterize the achievable rates for the model in Figure 1. Let $C_1 = 0.5 \log(1 + P/\sigma_1^2)$ and $C_2 = 0.5 \log(1 + P/\sigma_2^2)$. Since $\sigma_1^2 < \sigma_2^2$, $C_1 > C_2$.

Theorem 1: All rates R such that $0 < R < C_1$ are achievable for a Gaussian wiretap channel such that the probability of decoding error $P_e^n(B)$, at Bob goes to zero and the probability of decoding error $P_e^n(E)$, at Eve goes to one as, $n \to \infty$.

Proof: Consider the region $C_2 < R < C_1$. In this region, as in the case of a usual Gaussian channel, we generate n length iid Gaussian codewords with $X \sim \mathcal{N}(0, P)$. It can be proved using the channel coding theorem for the Gaussian channel [5] that any rate $R < C$ can be achieved for the Gaussian channel from Alice to Bob. The condition $R < C_1$ ensures reliable communication from Alice to Bob ensuring that $P_e^n(B) \to 0$ exponentially as $n \to \infty$. Also since $R > C_2$, by the strong converse to the coding theorem [1], [18] the average probability of decoding error for any decoder goes to one exponentially as $n \to \infty$. As this happens for any codebook, it is valid for the chosen codebook that gives reliable communication from Alice to Bob.

Now consider the region $0 < R < C_1$. In this region we use coding-decoding schemes as above but with reduced power αP, $0 < \alpha < 1$ such that $0.5 \log(1 + \alpha P/\sigma_2^2) < R < 0.5 \log(1 + \alpha P/\sigma_1^2)$. This ensures that we achieve reliable transmission to Bob and secrecy at Eve. ■

From Theorem 1 any rate $0 < R < C$ is achievable with Bob getting the message reliably and eve's probability of error as large as we wish. The block length n should be chosen large enough to satisfy any target probability of error to Bob and Eve. This improves the rate over the secrecy capacity definition based on equivocation ([14]):

$$C = 0.5 \log(1 + P/\sigma_1^2) - 0.5 \log(1 + P/\sigma_2^2). \qquad (1)$$

The equivocation based secrecy systems employ a stochastic encoder whereas in our scheme all rates $0 < R < C_1$ can be achieved by the usual encoders employing random codebooks (in practice one can use LDPC and Turbo codes to obtain rates close to C_1). For equivocation based schemes also one can get the required probability of error to Bob and Eve by ensuring large enough block length n. However the rate obtained can be quite low and it requires more complex encoders.

For $\sigma_1^2 = 0.1$, $\sigma_2^2 = 1.5$, and $P = 20dB$, $P_e^n(B)$ and $P_e^n(E)$ are plotted in Fig 2 for $n = 50$; 100 and 200. In this example the range of α over which we can achieve secrecy rate is $0.1474 < \alpha < 1$.

A nice geometrical interpretation of channel coding over an AWGN channel as a sphere packing problem along with upper and lower bounds was provided by Shannon in [21]. By similar geometric argument, for the channel from Alice to Bob the received vectors at Bob have energy no greater than $n(P + \sigma_1^2) + \delta$ and they lie in an n-dimensional sphere of radius $\sqrt{n(P + \sigma_1^2) + \delta}$ for n large enough with a high probability, where δ is a small positive constant. In the following for simplicity we ignore δ and consider large n. Each decoding sphere (sphere such that if the received vector lies in it, it will be decoded as a particular codeword) for a small probability of error has a radius of $\sqrt{n\sigma_1^2}$ and the maximum number of non-intersecting spheres in this volume are $\left(1 + \frac{P}{\sigma_1^2}\right)^{\frac{n}{2}}$. Hence for $R < C_1 = 0.5 \log(1 + P/\sigma_1^2)$, each decoding sphere uniquely represents a codeword with a large probability and $P_e^n(B) \to 0$ as $n \to \infty$. However we have $R > C_2$ for Eve and the received codewords lie in a sphere of radius $\sqrt{n(P + \sigma_2^2)}$ and the decoding spheres for a



Fig. 2. Probability of error vs α

low probability of error should have radius $\sqrt{n\sigma_2^2}$. Thus, the decoding spheres overlap at the eavesdropper. As $n \to \infty$, the number of overlapping decoding spheres also approach infinity and hence $P_e^n(E) \to 1$. This overlapping creates confusion at Eve and can be viewed as an equivalent of superposition codes used to confuse Eve in equivocation based secrecy systems ([14], [3]).

IV. RELATION BETWEEN PROBABILITY OF ERROR AND EQUIVOCATION

In this section we compare the secrecy criterion based on just probability of error with the usual criterion based on equivocation.

When $C_2 < R < C_1$, $P_e^n(B) \to 0$, exponentially and $P_e^n(E) \to 1$ exponentially. Thus, Fano's inequality [5]

$$H(W|Y^n) \leq H(P_e^n(B)) + P_e^n(B)nR \tag{2}$$

gives $H(W|Y^n) \to 0$ almost exponentially where $H(p) = -p\log(p) - (1-p)\log(1-p)$. Similarly, the upper bound (2) for $H(|Z^n)$ goes to nR exponentially.

From [8] we get more refined results. For Bob, for any $0 \leq \rho \leq 1$,

$$H(W|Y^n) \leq (1 + \frac{1}{\rho})e^{-n[E_0(\rho,p)-\rho R]} \tag{3}$$

where p is the distribution of X and $E_0(\rho,p)$ is the Gallager's random coding bound ([10])

$$E_0(\rho,p) = -\log\left(\int_y \left(\int_x p(x)p(y|x)^{\frac{1}{1+\rho}}dx\right)^{1+\rho} dy\right) \tag{4}$$

and $p(y|x)$ is the channel transition function. Thus, $H(W|Y^n) \to 0$ exponentially. For Eve, since $I(W;Z^n) \leq nC_2$, $\frac{1}{n}H(W \mid Z^n) \geq R - C_2$ for all codebooks.

A more accurate lower bound on $H(W \mid Z^n)$ can be obtained from Theorem 1, [8],

$$H(W|Z^n) \geq \phi^*(\pi(W|Z^n)), \tag{5}$$

where ϕ^* is a piecewise linear, continuous, non-decreasing, convex function provided in [8] and $\pi(W|Z^n)$ is the average probability of error for the MAP decoder at Eve. $\pi(W|Z^n)$ in (5) can be replaced by the Arimoto's lower bound ([1])

$$\pi(W|Z^n) \geq 1 - e^{-n(E_0(\rho,p)-\rho R)}, \quad 0 > \rho > -1. \tag{6}$$

Minimizing the exponent with respect to p and maximizing w.r.t ρ provides a universal lower bound.

V. FADING CHANNEL

A fading wiretap channel model can be mathematically represented as:

$$Y_i = h_i X_i + N_{1i}, \tag{7}$$

$$Z_i = g_i X_i + N_{2i}, \tag{8}$$

where h_i, g_i are the normalized complex channel gains from Alice to Bob and Eve respectively at instant i. We assume that these gains are available at Alice, Bob and Eve. We take $\sigma_1^2 = \sigma_2^2 = 1$. Also denote the instantaneous power gains by $q(i) = |h(i)|^2$ and $r(i) = |g(i)|^2$. The rest of the model is same as in Section II. For this case the capacity achieving signalling scheme based on equivocation at Eve is to transmit at instances when $q > r$ and adapt the instantaneous power according to q and r. The capacity is [12]:

$$\begin{aligned} C_s &= \int_0^\infty \int_r^\infty [\log(1 + qP^*(q,r)) - \\ &\quad \log(1 + rP^*(q,r))]f(q)f(r)dqdr \end{aligned} \tag{9}$$

where $E[P^*(q,r)] = P$,

$$\begin{aligned} P^*(q,r) &= 0.5[\sqrt{(1/r - 1/q)^2 + 4/\lambda(1/r - 1/q)} + \\ &\quad (1/r + 1/q)]^+ \end{aligned} \tag{10}$$

and λ is chosen to satisfy the power constraint with equality.

Now we extend Theorem 1 to include fading. We use a scheme similar to that in [12] but with the condition $P_e^n(B) \to 0$ and $P_e^n(E) \to 1$ as $n \to \infty$.

Theorem2: All rates R such that $0 < R < C_1$ are achievable for a Gaussian wiretap channel such that the probability of decoding error, $P_e^n(B)$, at Bob goes to zero and the probability of decoding error, $P_e^n(E)$, at eve goes to one as, $n \to \infty$ where

$$C_1 = \sup_{P(q,r)} \int_0^\infty \int_r^\infty [\log(1 + qP(q,r))]f(q)f(r)dqdr. \tag{11}$$

.

The optimal power allocation is 'water-filling' w.r.t. the distribution of q conditioned on $q > r$.

Proof: Whenever $q > r$, we transmit data with power $P(q,r)$ and rate $0.5\log(1 + qp(q,r))$. We select $p(q,r)$ such that $0.5E_{q,r}[\log(1+qP(q,r))]$ is maximized. This is achieved by the above water filling policy. ■

VI. CONCLUSIONS

This paper uses a new notion of secrecy for improving the rates in a Gaussian wire-tap channel. This new notion is based on using probability of error as the measure of secrecy at both the intended receiver and also the eavesdropper. In such a set up, it is shown that the random codes used for point to point communication can be used to provide secrecy as well. Also it is shown that this notion of secrecy is weaker compared to the equivocation based secrecy. The results are also extended to a fading channel.

We believe that this notion of secrecy is strong enough for practical purposes, but uses usual channel code and provides the maximum possible rates for reliable transmission to the intended receiver.

Although we have shown these concepts on a Wiretap channel, these ideas can obviously be used on other channels as well.

REFERENCES

[1] S. Arimoto, "On the Converse to the Coding Theorem for Discrete Memoryless Channels," *IEEE Trans. Inform. Theory.*, vol. 19, no. 3, pp. 357 359, May 1973.

[2] J. C. Belfiore and F. Oggier, "Secrecy Gain: a Wiretap Lattice Code Design," *ISITA 2010*, Available : http://arxiv.org/abs/1004.4075.

[3] M. Bloch and J. Barros, "Physical layer security," *Cambridge Univ. Press*, 2011.

[4] M. Bloch, J. Barros, M.R.D. Rodrigues, S.W. McLaughlin, "Wireless information-theoretic security," *IEEE Transactions on Information Theory*, vol. 54, no. 6, pp. 2515–2534, June 2008.

[5] T. Cover and J.A. Thomas, "Elements of information theory," *John Wiley and Sons*, 2ed., 2006.

[6] I. Csiszàr and J.Korner, "Broadcast channels with confidential messages," *IEEE Transactions on Information Theory*, vol. 82, no. 23, pp. 339–348, May 1978.

[7] R. M. Fano, "Transmission of Information," *MIT press*, 1961.

[8] M. Feder and N. Merhav, "Relations Between Entropy and Error Probability," *IEEE Trans. Inform. Theory.*, VOL. 40, NO. 1, Jan. 1994.

[9] A. Feinstein, " Foundations of information theory," *McGraw-Hill, N.Y.*, 1954.

[10] R. G. Gallagar, "Information Theory and Reliable Communication," *John Wiley and Sons*, 1968.

[11] A. J. Goldsmith and P. P. Varia, "Capacity of Fading Channels with Channel Side Information," *IEEE Trans. Inform. Theory.*, Vol. 43, No. 6, Nov. 1997.

[12] P. K. Gopala, L. Lai, H. El Gamal, "On the secrecy capacity of fading channels," *IEEE Trans. Info. Theory*, vol. 54, no. 10, pp. 4687–4698, October 2008.

[13] S. W. Ho and S. Verdu, "On the Interplay Between Conditional Entropy and Error Probability," *IEEE Trans. Inform. Theory.*, Vol. 56, No. 12, Dec. 2010.

[14] Y. Liang, H. V. Poor, S. Shamai, "Information theoretic security," *Foundations and Trends in Communications and Information Theory*, vol. 5, no. 4-5 (2008), pp. 355–580, 2009.

[15] S. K. Leung-Yan-Cheong and M. E. Hellman, "Gaussian wire-tap channel," *IEEE Transactions on Information Theory*, vol. 82, no. 24 (4), pp. 451–456, July 1978.

[16] U. M. Maurer and S. Wolf, "Information-theoretic key agreement: From weak to strong secrecy for free," *Proceedings of the EUROCRYPT 2000 on Advances in Cryptology,*, vol. 1807, pp. 352368, Lecture Notes in Computer Science, Berlin, Germany: Springer, 2000.

[17] A. J. Menezes, P. C. V. Oorschot, and S. A. Vanstone, "Handbook of applied cryptography," *Boca Raton, FL, USA: CRC Press*, 1996.

[18] Y. Polyanskiy and S. Verdu, "Arimoto Channel Coding Converse and Renyi Divergence," *48 Annual Allerton Conference*, Monticello, IL, 2010.

[19] C. E. Shannon, "A mathematical theory of communication," *Bell System Technical Journal*, vol. 27, pp. 379423, 623-656, July, October, 1948.

[20] C. E. Shannon, "Communication of secrecy systems," *Bell Syst. Tech. J.*, vol. 28, pp. 656-715, October 1949.

[21] C. E. Shannon, "Probability of error for optimal codes in a Gaussian channel," *Bell system Technical Journal.*, Vol. 38, No. 3, May 1959.

[22] J. Wolfowitz, "Codinq Theorems of Information Theory," *Prentice-Hall N J*, 2 ed Engelwood Cliffs, 1964.

[23] A. Wyner, "The wire-tap channel," *Bell Syst. Tech. J.*, vol. 54, pp. 1355-1387, 1974.